

97-AR420	電氣規格表	ELECTRONIC SPECIFICATIONS
-----------------	--------------	----------------------------------

機種 MODEL	AR420	客戶 CUSROMER	PROART
-----------------	-------	--------------------	--------

DESCRIPTIONS / 品名	HI-END Power Amplifier
--------------------------	-------------------------------

NO	DESCRIPTIONS	TEST CONDITIONS	UNIT	NOM	LIMIT	TEST RECORD
1	POWER OUTPUT 輸出功率	Load	< 1% THD	W	400	>400
		4 Ohms	< 10% THD	W	500	>500
		Load	< 1% THD	W	250	>240
		8 Ohms	< 3% THD	W	280	>280
		Load/Bridged	< 1% THD	W	500	>500
		8 Ohms	< 10% THD	W	550	>550
2	GAIN 總增益		LINE IN	db	25	+/-3
			MIC IN	db		
3	FREQUENCY RESP 頻率響應	(-1db)	LINE IN	Hz	10-60K	15-50K
			MIC IN	Hz		
4	TONE CONTROL 高低音響控制		BASS	db		
			TREBLE	db		
5	OUTPUT IMPEDANCE 輸出組抗			Ohms	4/8	
				Ohms		
6	INPUT IMPEDANCE 輸入組抗			Ohms	30K	>30K
				Ohms		
7	NOISE 雜音指數		VR MIN	mv		
			VR MIX	mv	0.05	<0.1
8	T.H.D 總失真度				0.005	<0.005
			1WATT	%		
9	HUM 交流雜音		VR MIN	db		
			VR MIX	db	105	>105

作業及外觀檢點	CHECK ASSY' & PARTS SPECIFICATIONS
----------------	---

1.一般AMPLIFIER標準	

	版本及日期	確認	製成
	A/0		

TEL:03-369-1588 / 369-9195 FAX:3699281

