

Model	Specifications
-------	----------------

Model no.	PA6200 A/D	120/240W	100V	Microphone Mixer Amplifier
-----------	------------	----------	------	----------------------------



Features:

Specifications

- Class A/B Power Amplifier
- 0.50.70.100V High Voltage Output .
- 5 Zone 100V Output Selectot.
- Signal Input LED Indicator.
- Peak & Protect LED Indicator.
- Tone Bass Treble Function.
- Aux1/2 Input Rec. Output.
- Microphone 1/2/3 T.R.S Jack.
- X.L.R Microphone Input.
- RCA Unbalanced Input.
- Voltage Selector 115V/230V Switch.
- IEC AC Outlet & Power Input.

- Power Output (At 8 Ohms < 1%):
A= 70W D=150W
- Power Output (At 4 Ohms < 1%):
A=120W D=240W
- Distortion: < 0.05 %
- S/N Ratio (IEC-A): > 90db .
- Microphone Sensitivity: -70 dbu.
- Aux Input Sensitivity: -40dbu
- Maximum Input: >4V. (AUX)
- Frequency Response (+/- 1db) :20-20KHz.
- Dimensions: 420*88*300 mm(W*H*D).
- Weight: 7 / 9Kgs (Net).